

NAG Library Function Document

nag_sum_fft_sine (c06rec)

1 Purpose

nag_sum_fft_sine (c06rec) computes the discrete Fourier sine transforms of m sequences of real data values. The elements of each sequence and its transform are stored contiguously.

2 Specification

```
#include <nag.h>
#include <nagc06.h>
void nag_sum_fft_sine (Integer m, Integer n, double x[], NagError *fail)
```

3 Description

Given m sequences of $n - 1$ real data values x_j^p , for $j = 1, 2, \dots, n - 1$ and $p = 1, 2, \dots, m$, nag_sum_fft_sine (c06rec) simultaneously calculates the Fourier sine transforms of all the sequences defined by

$$\hat{x}_k^p = \sqrt{\frac{2}{n}} \sum_{j=1}^{n-1} x_j^p \times \sin\left(jk\frac{\pi}{n}\right), \quad k = 1, 2, \dots, n - 1 \text{ and } p = 1, 2, \dots, m.$$

(Note the scale factor $\sqrt{\frac{2}{n}}$ in this definition.)

This transform is also known as type-I DST.

Since the Fourier sine transform defined above is its own inverse, two consecutive calls of nag_sum_fft_sine (c06rec) will restore the original data.

The transform calculated by this function can be used to solve Poisson's equation when the solution is specified at both left and right boundaries (see Swarztrauber (1977)).

The function uses a variant of the fast Fourier transform (FFT) algorithm (see Brigham (1974)) known as the Stockham self-sorting algorithm, described in Temperton (1983), together with pre- and post-processing stages described in Swarztrauber (1982). Special coding is provided for the factors 2, 3, 4 and 5.

4 References

Brigham E O (1974) *The Fast Fourier Transform* Prentice–Hall

Swarztrauber P N (1977) The methods of cyclic reduction, Fourier analysis and the FACR algorithm for the discrete solution of Poisson's equation on a rectangle *SIAM Rev.* **19(3)** 490–501

Swarztrauber P N (1982) Vectorizing the FFT's *Parallel Computation* (ed G Rodrigue) 51–83 Academic Press

Temperton C (1983) Fast mixed-radix real Fourier transforms *J. Comput. Phys.* **52** 340–350

5 Arguments

1: **m** – Integer *Input*

On entry: m , the number of sequences to be transformed.

Constraint: $m \geq 1$.

- 2: **n** – Integer *Input*
On entry: one more than the number of real values in each sequence, i.e., the number of values in each sequence is $n - 1$.
Constraint: $n \geq 1$.
- 3: **x**[(**n** – 1) × **m**] – double *Input/Output*
On entry: the p th sequence to be transformed, denoted by x_j^p , for $j = 1, 2, \dots, n - 1$ and $p = 1, 2, \dots, m$, must be stored in $\mathbf{x}[(p - 1) \times (n - 1) + j - 1]$.
On exit: the m Fourier sine transforms, overwriting the corresponding original sequences. The $(n - 1)$ components of the p th Fourier sine transform, denoted by \hat{x}_k^p , for $k = 1, 2, \dots, n - 1$ and $p = 1, 2, \dots, m$, are stored in $\mathbf{x}[(p - 1) \times (n - 1) + k - 1]$.
- 4: **fail** – NagError * *Input/Output*
The NAG error argument (see Section 2.7 in How to Use the NAG Library and its Documentation).

6 Error Indicators and Warnings

NE_ALLOC_FAIL

Dynamic memory allocation failed.

See Section 2.3.1.2 in How to Use the NAG Library and its Documentation for further information.

NE_BAD_PARAM

On entry, argument *<value>* had an illegal value.

NE_INT

On entry, **m** = *<value>*.

Constraint: $m \geq 1$.

On entry, **n** = *<value>*.

Constraint: $n \geq 1$.

NE_INTERNAL_ERROR

An internal error has occurred in this function. Check the function call and any array sizes. If the call is correct then please contact NAG for assistance.

An unexpected error has been triggered by this function. Please contact NAG.

See Section 2.7.6 in How to Use the NAG Library and its Documentation for further information.

NE_NO_LICENCE

Your licence key may have expired or may not have been installed correctly.

See Section 2.7.5 in How to Use the NAG Library and its Documentation for further information.

7 Accuracy

Some indication of accuracy can be obtained by performing a subsequent inverse transform and comparing the results with the original sequence (in exact arithmetic they would be identical).

8 Parallelism and Performance

nag_sum_fft_sine (c06rec) is threaded by NAG for parallel execution in multithreaded implementations of the NAG Library.

Please consult the x06 Chapter Introduction for information on how to control and interrogate the OpenMP environment used within this function. Please also consult the Users' Note for your implementation for any additional implementation-specific information.

9 Further Comments

The time taken by `nag_sum_fft_sine` (c06rec) is approximately proportional to $nm\log(n)$, but also depends on the factors of n . `nag_sum_fft_sine` (c06rec) is fastest if the only prime factors of n are 2, 3 and 5, and is particularly slow if n is a large prime, or has large prime factors. Workspace is internally allocated by this function. The total amount of memory allocated is $O(n)$ double values.

10 Example

This example reads in sequences of real data values and prints their Fourier sine transforms (as computed by `nag_sum_fft_sine` (c06rec)). It then calls `nag_sum_fft_sine` (c06rec) again and prints the results which may be compared with the original sequence.

10.1 Program Text

```

/* nag_sum_fft_sine (c06rec) Example Program.
 *
 * NAGPRODCODE Version.
 *
 * Copyright 2016 Numerical Algorithms Group.
 *
 * Mark 26, 2016.
 */

#include <nag.h>
#include <stdio.h>
#include <nag_stdlib.h>
#include <nagc06.h>

int main(void)
{
    /* Scalars */
    Integer exit_status = 0, j, m, n, n1;
    /* Arrays */
    double *x = 0;
    char title[60];
    /* Nag Types */
    NagError fail;

    INIT_FAIL(fail);

    printf("nag_sum_fft_sine (c06rec) Example Program Results\n");
    fflush(stdout);

    /* Read dimensions of array from data file. */
#ifdef _WIN32
    scanf_s("%*[^\\n] %" NAG_IFMT "%" NAG_IFMT "%*[^\\n]", &m, &n1);
#else
    scanf("%*[^\\n] %" NAG_IFMT "%" NAG_IFMT "%*[^\\n]", &m, &n1);
#endif

    n = n1 + 1;

    if (!(x = NAG_ALLOC((m * n1), double)))
    {
        printf("Allocation failure\n");
        exit_status = -1;
        goto END;
    }

    /* Read array values from data file and print out. */
    for (j = 0; j < m * n1; j++)

```

```

#ifdef _WIN32
    scanf_s("%lf", &x[j]);
#else
    scanf("%lf", &x[j]);
#endif
#ifdef _WIN32
    sprintf_s(title, (unsigned)_countof(title), "\n Original data values\n");
#else
    sprintf(title, "\n Original data values\n");
#endif
nag_gen_real_mat_print_comp(Nag_RowMajor, Nag_GeneralMatrix,
                            Nag_NonUnitDiag, m, n1, x, n1, "%9.4f",
                            title, Nag_NoLabels, 0, Nag_NoLabels,
                            0, 80, 0, NULL, &fail);
if (fail.code != NE_NOERROR) {
    printf("Error from nag_gen_real_mat_print_comp (x04cbc).\n%s\n",
          fail.message);
    exit_status = 1;
    goto END;
}

/* nag_sum_fft_sine (c06rec).
 * Discrete sine transforms
 */
nag_sum_fft_sine(m, n, x, &fail);
if (fail.code != NE_NOERROR) {
    printf("Error from nag_sum_fft_sine (c06rec).\n%s\n", fail.message);
    exit_status = 2;
    goto END;
}

#ifdef _WIN32
    sprintf_s(title, (unsigned)_countof(title),
              "\n Discrete Fourier sine transforms\n");
#else
    sprintf(title, "\n Discrete Fourier sine transforms\n");
#endif
nag_gen_real_mat_print_comp(Nag_RowMajor, Nag_GeneralMatrix,
                            Nag_NonUnitDiag, m, n1, x, n1, "%9.4f",
                            title, Nag_NoLabels, 0, Nag_NoLabels,
                            0, 80, 0, NULL, &fail);
if (fail.code != NE_NOERROR) {
    printf("Error from nag_gen_real_mat_print_comp (x04cbc).\n%s\n",
          fail.message);
    exit_status = 3;
    goto END;
}

/* Two consecutive calls should restore the original data. */
nag_sum_fft_sine(m, n, x, &fail);
if (fail.code != NE_NOERROR) {
    printf("Error from nag_sum_fft_sine (c06rec).\n%s\n", fail.message);
    exit_status = 4;
    goto END;
}

#ifdef _WIN32
    sprintf_s(title, (unsigned)_countof(title),
              "\n Original data as restored by inverse transform\n");
#else
    sprintf(title, "\n Original data as restored by inverse transform\n");
#endif
nag_gen_real_mat_print_comp(Nag_RowMajor, Nag_GeneralMatrix,
                            Nag_NonUnitDiag, m, n1, x, n1, "%9.4f",
                            title, Nag_NoLabels, 0, Nag_NoLabels,
                            0, 80, 0, NULL, &fail);
if (fail.code != NE_NOERROR) {
    printf("Error from nag_gen_real_mat_print_comp (x04cbc).\n%s\n",
          fail.message);
    exit_status = 5;
    goto END;
}

```

```

    }
END:
    NAG_FREE(x);
    return exit_status;
}

```

10.2 Program Data

nag_sum_fft_sine (c06rec) Example Program Data

```

3      5                                     : m, n-1

0.6772  0.1138  0.6751  0.6362  0.1424
0.2983  0.1182  0.7255  0.8638  0.8723
0.0644  0.6037  0.6430  0.0428  0.4815 : x

```

10.3 Program Results

nag_sum_fft_sine (c06rec) Example Program Results

Original data values

0.6772	0.1138	0.6751	0.6362	0.1424
0.2983	0.1182	0.7255	0.8638	0.8723
0.0644	0.6037	0.6430	0.0428	0.4815

Discrete Fourier sine transforms

1.0014	0.0062	0.0834	0.5286	0.2514
1.2478	-0.6598	0.2570	0.0858	0.2658
0.8521	0.0719	-0.0561	-0.4890	0.2056

Original data as restored by inverse transform

0.6772	0.1138	0.6751	0.6362	0.1424
0.2983	0.1182	0.7255	0.8638	0.8723
0.0644	0.6037	0.6430	0.0428	0.4815
